



Ahuja BTA-880-PA Portable Amplifier Set

Product Specification

Brand	Ahuja
Model	BTA-880-PA
Type	Portable Amplifier Set
Input Channels	2 x Mic 3mV/4.7k Ω , 1 x Aux 100mV/47k Ω , Music 100mV/47k Ω , 2 x Wireless MIC
Frequency Response	55-18,000Hz \pm 3dB (Bi-Amp)
S/N Ratio	60dB
Tone Controls	Bass \pm 5dB at 100Hz, Treble \pm 5dB at 10kHz
Digital Player	MP3 player with USB, SD, MMC card reader, Recording function and Bluetooth
Preamp Output	200mV/600 Ω
Speaker	1 \times 12 Speaker 1xHF Driver
Wireless Microphone	2 x Hand Held
Frequency Stability	\pm 0.005%
Max. Modulation	45dB
RF Output Power	10mW
Frequency Response	50-15,000Hz
Battery	3V (2 \times 1.5V AA Pencil Cells)

Current Consumption	< 200mA
---------------------	---------